

uitgangsspanning en -stroom in verhouding tot vermogen

P_{eff} (W)	$R_L = 4 \Omega$				$R_L = 8 \Omega$			
	U_{eff} (V)	U_t (V)	I_{eff} (A)	I_t (A)	U_{eff} (V)	U_t (V)	I_{eff} (A)	I_t (A)
1.0	2.00	2.83	0.50	0.71	2.83	4.00	0.35	0.50
1.5	2.45	3.46	0.61	0.87	3.46	4.90	0.43	0.61
2.0	2.83	4.00	0.71	1.00	4.00	5.66	0.50	0.71
2.5	3.16	4.47	0.79	1.12	4.47	6.32	0.56	0.79
3.0	3.46	4.90	0.87	1.22	4.90	6.93	0.61	0.87
3.5	3.74	5.29	0.94	1.32	5.29	7.48	0.66	0.94
4.0	4.00	5.66	1.00	1.41	5.66	8.00	0.71	1.00
4.5	4.24	6.00	1.06	1.50	6.00	8.49	0.75	1.06
5.0	4.47	6.32	1.12	1.58	6.32	8.94	0.79	1.12
5.5	4.69	6.63	1.17	1.66	6.63	9.38	0.83	1.17
6.0	4.90	6.93	1.22	1.73	6.93	9.80	0.87	1.22
7.0	5.29	7.48	1.32	1.87	7.48	10.58	0.94	1.32
8.0	5.66	8.00	1.41	2.00	8.00	11.31	1.00	1.41
9.0	6.00	8.49	1.50	2.12	8.49	12.00	1.06	1.50
10.0	6.32	8.94	1.58	2.24	8.94	12.65	1.12	1.58
12.0	6.93	9.80	1.73	2.45	9.80	13.86	1.22	1.73
15.0	7.75	10.95	1.94	2.74	10.95	15.49	1.37	1.94
20.0	8.94	12.65	2.24	3.16	12.65	17.89	1.58	2.24
25.0	10.00	14.14	2.50	3.54	14.14	20.00	1.77	2.50
30.0	10.95	15.49	2.74	3.87	15.49	21.91	1.94	2.74
35.0	11.83	16.73	2.96	4.18	16.73	23.66	2.09	2.96
40.0	12.65	17.89	3.16	4.47	17.89	25.30	2.24	3.16
45.0	13.42	18.97	3.35	4.74	18.97	26.83	2.37	3.35
50.0	14.14	20.00	3.54	5.00	20.00	28.28	2.50	3.54
60.0	15.49	21.91	3.87	5.48	21.91	30.98	2.74	3.87
70.0	16.73	23.66	4.18	5.92	23.66	33.47	2.96	4.18
80.0	17.89	25.30	4.47	6.32	25.30	35.78	3.16	4.47
90.0	18.97	26.83	4.74	6.71	26.83	37.95	3.35	4.74
100.0	20.00	28.28	5.00	7.07	28.28	40.00	3.54	5.00
120.0	21.91	30.98	5.48	7.75	30.98	43.82	3.87	5.48
150.0	24.49	34.64	6.12	8.66	34.64	48.99	4.33	6.12
200.0	28.28	40.00	7.07	10.00	40.00	56.57	5.00	7.07
300.0	34.64	48.99	8.66	12.25	48.99	69.28	6.12	8.66
400.0	40.00	56.57	10.00	14.14	56.57	80.00	7.07	10.00